

**PLM-AL-5V**

Micro transformer 24-12V / 5V DC 1000mA

Micro power supply 24-12V DC 1000 mA with excellent stabilized voltage for powering any type of GSM bug and 5V spy camera (max absorption 1000 mA).

To view the product video [click here](#)



The small dimensions of the micro transformer (just 25 x 17 x 8 mm) allows it to be easily hidden inside electrical systems in homes or cars to power a GSM bug.

It features high-efficiency switching technology that allows compact dimensions and high voltage stability in case of absorption changes. Also the heat dissipation is minimized.

## PLM-AL-5V

### FEATURES:

- Ultra-compact size
- Constant voltage output
- Overload and short circuit protection
- High efficiency thanks to switching technology
- Ideal for concealment even in small spaces

### INPUT SPECS:

- Input voltage 24-12V DC
- No-load consumption 5mA

### OUTPUT SPECIFICATIONS:

- Deliverable power 5W
- Efficiency > 80%
- Typical switching regulation frequency 70kHz
- Output voltage error <1%
- Ripple and noise 200mV max

### SPECIFICATIONS:

- Operating temperature - 65° / + 150°C
- Output current: 3A (max)  
Short-circuit and overheating protection with auto restart
- Undervoltage protection
- Operating humidity 5% - 95% RH
- Italian quality, CE marking
- Dimensions 25 x 17 x 8 mm
- Weight: 10 gr.